



Product Data Sheet: FlatMesh Optical Displacement Sensor Node

The FlatMesh Optical Displacement Sensor Node is an instrument which uses optical means to take high precision displacement measurements and pass these through Senceive's FlatMesh wireless communications network to a FlatMesh Gateway.

It can also be combined with Senceive's world-leading triaxial tilt sensor to obtain high precision tilt measurements that are linked to an external reference.

Optical Displacement sensing is perfect for many applications, including those measuring:

- Convergence/divergence for Tunnel/Arch intrados or bridge abutments
- Vertical movements for structural settlement/heave
- Lateral movements such as rail track slew
- Earthworks and embankment movement



Key Features

- Fully integrated unit
- Extremely low noise performance
- Optical sensor resolution of 0.1mm and repeatability of $\pm 0.15\text{mm}$
- Resolution of 0.0001° (0.0018mm/m) and repeatability of $\pm 0.0005^\circ$ ($\pm 0.009\text{mm/m}$)
- Integrated long life battery
- 10 years battery life, including when acting as a relay node within the mesh communications network
- Easy to align with target when using the magnet triggered aiming mode
- Integrated temperature sensor
- Versatile mounting options
- Waterproof to IP66 / IP67 / IP68
- Firmware is remotely upgradeable over the air via the gateway reducing costly site visits

CONTACT US

Specifications

Physical Specifications

Dimensions	90 x 90 x 60 mm 90 x 96 x 60 mm (including vent)
Total Mass	0.6 kg (approx.)
Housing Material	Die cast aluminium body
International Protection Marking	IP66 / IP67 IP68 (1m for 24 hours)
Mounting Options	Clearance holes for M4 socket head screw in bottom, M4 blind holes in side Plates and brackets available for magnetic fixing, track bed, stake and pole mounting, and many other applications
Operating Temperature Range	-10°C to +50°C (full functionality) -25°C to +70°C (mesh radio, temperature and tilt only)

FlatMesh Radio Specifications

Communication Type	Proprietary FlatMesh v3 Mesh Networking Protocols IEEE 802.15.4 compliant
Frequency Band	2400 - 2485 MHz ISM Band
Maximum Transmit Power	6.5dBm (EN 300 328 v1.8.1)
Maximum Antenna Gain	2.2dBi
Range	Up to 300m depending on the environment and fitted antenna Consult with Senceive for your application
RF Module	Senceive FM3Node

Optical Sensor Specifications

Resolution	0.1mm
Repeatability	±0.15mm
Range	50 metres (natural surface) 100 metres (white target) 150 metres (reflecting target)
Laser Type	Class 2, 655nm (visible red)

Tilt Sensor Specification

Resolution	0.0001° (0.00175mm/m)
Repeatability (-IX variant)	±0.0005° (±0.0087mm/m)
Repeatability (-IXH variant)	±0.0025° (±0.0436mm/m)
Range	±90°

CONTACT US

For information on our award-winning wireless asset condition monitoring solutions, call **+44 (0) 207 731 8269**, email **info@senceive.com**, visit

www.senceive.com

Senceive Ltd, Imperial Studios, Imperial Wharf, London, SW6 2AG, United Kingdom

Internal Battery

Battery Type	Lithium Thionyl Chloride, non-rechargeable
Nominal Voltage	3.6V
Nominal Capacity	19000mAh
Typical Battery Life	10 years at 1 hour reporting interval, including when acting as a relay node 8years at 30minute reporting interval, including when acting as a relay node Battery life may be reduced when measuring to poorly reflecting surfaces Consult with Senceive for your application

Certifications

- Tested to conformity with all the essential requirements of the Radio Equipment Directive 2014/53/EU and RoHS Directive 2011/65/EU
- FCC Grant of Equipment Authorization: FCC ID 2AMFBFM3N
- RCM (Australia and New Zealand)

CONTACT US

For information on our award-winning wireless asset condition monitoring solutions, call **+44 (0) 207 731 8269**, email **info@senceive.com**, visit **www.senceive.com**

Ordering Information and Accessories

FM3N-LDS-IX	FlatMesh 3 Optical Displacement Sensor with integrated Triaxial Tilt Sensor
FM3N-LDS-IXH	FlatMesh 3 Optical Displacement Sensor with integrated Triaxial Tilt Sensor (High-G)
FF-MP-S360	Swivel mounting kit with 360-degree adjustment range Screw directly to vertical walls
FF-MP-V	Vertical mounting plate Use U-bolts to fix to poles or stakes Use glue to fix to walls where drilling is not permitted (Order with FF-MP-S360)
FF-MP-RA	Right angle mounting bracket Screw to concrete tunnel linings and inclined walls (Order with FF-MP-S360)
FF-MP-T2	Track bed mounting plate kit
FF-MP-M2	Magnetic mounting kit High degree of adjustability, perfect for cast iron lined tunnels
FA-FM-WPS	Waterproof straight antenna Overall node height 168mm (approx) when fitted Maximum gain +1.1dBi
FA-FM-LPS	Waterproof low profile straight antenna Minimum overall node height, perfect for track bed and tight spots Overall node height 92mm (approx) when fitted Maximum gain 0dBi
FA-FM-ADJ	Adjustable angle antenna Flexible installation, perfect for use in tunnels and indoor environments Overall node height 202mm (approx) when fitted and upright Overall node height 102mm (approx) when fitted and at 90-degree angle Maximum gain +2dBi
FC-NC	Antenna cover kit Use with FA-FM-LPS antenna Overall node height 96mm (approx) when fitted

CONTACT US

For information on our award-winning wireless asset condition monitoring solutions, call **+44 (0) 207 731 8269**, email **info@senceive.com**, visit **www.senceive.com**